

Impedance Matching Volume Controls

- Allows multiple pairs of speakers to be used with an amplifier.
- Adjustable impedance jumpers allow as many as eight pairs of 8-ohm speakers to be driven by a single 8-ohm capable amplifier.
- Features 12 control positions, soft-touch action and silent switching capability.



VC60SIM

Speaker Impedance	8 ohms
Amplifier Impedance	8 ohms (X1 setting); 16 ohms (X2 setting); 32 ohms (X4 setting); 64 ohms (X8 setting)
Connections	Removable 4-pin screw connectors simplify speaker and amplifier wiring (14 AWG wire capacity).
Frequency Response	20Hz - 20kHz \pm 1dB
Power Handling	60W RMS max input/channel
Design	Slider (includes Decora wallplate)
Shipping Weight	2 lbs (0.9kg)