



Chrysler LOC (Line Output Converter) **AXLOC-CH5** (for Non-Amplified Vehicles) **2013-Up**

Visit AxxessInterfaces.com for more detailed information about the product and up-to-date vehicle specific applications.

INTERFACE FEATURES

- Designed to provide (2) channels of low-level audio output from the factory system.
- Allows for the installation of an amplifier for speakers or subwoofers.
- Gain Controller included to adjust the overall output.
- 12v-500mA remote wire activated with signal sense.
- 55-watts per channel.
- Designed for non-amplified vehicles.

Note: A single pole double throw (SPDT) relay is recommended when installing multiple amplifiers.

INTERFACE COMPONENTS

- AXLOC-CH5 Wiring Harness
- Gain Controller
- 12v-500mA Remote Wire
- Auxiliary Cable
- Load Resistors: RPAD-20, RPAD-39, RPAD-60

APPLICATIONS

Chrysler	Fiat	Jeep	Ram
200	2015-2017	500	2016-2019
Pacifica	2017-2020	500L	2014-2020
Dodge		500X	2016-Up
Dart	2011-2014		Cherokee
Durango	2011-2020		Compass
1500, 2500, 3500	2013-Up		Renegade
			Wrangler (JL)
			2013-Up
			2017-Up
			2015-Up
			2018.5-Up
			Chassis Cab
			2500/3500/4500/5500
			2013-Up
			Promaster
			1500/2500/3500
			Promaster City
			2014-Up
			2015-Up

For dash disassembly instructions, refer to metraonline.com. Enter the year, make, and model of the vehicle in the **Vehicle Fit Guide** for **Radio Install Kits**.

SALES 386-257-2956

REV. 2/23/23