


marantz®



M-CR612 NETWORK CD RECEIVER FEATURING HEOS, FM/AM, BLUETOOTH®, AIRPLAY 2 AND VOICE CONTROL COMPATIBILITY

The Marantz M-CR612 compact network CD receiver supports near limitless streaming platforms through AirPlay2, Bluetooth and HEOS connectivity. The built-in disc player is compatible with music CDs, CD-R/CD-RW recordable and erasable discs, and is equipped with an AM/FM tuner. Use your voice to control the M-CR612 with Amazon Alexa, Google Assistant or Apple Siri for seamless ease of use.

Highlights

- Power and connectivity to suit your audio preference: 60W x 2ch (6 ohms), or 4x 30W for speaker A/B with individual volume setting
- Plays CD, WMA/MP3 (CD-R/RW) and features an AM/FM tuner: No matter how you listen, enjoy your music with elevated Marantz sound
- Stream music from your favorite sources: Play songs from TuneIn internet radio, Pandora, Spotify, SiriusXM, Amazon Prime Music, TIDAL and more via AirPlay 2, Bluetooth and the HEOS app (music streaming services may vary by region)
- Supports Amazon Alexa, Google Assistant and Apple Siri voice agents: Use your voice to control the M-CR612
- High-performance, high-resolution audio playback for every source: Supports WAV/FLAC/ALAC 192kHz/24bit, DSD 2.8/5.6MHz and Gapless playback (WAV/FLAC/ALAC, DSD)
- Built-in Bluetooth and Wi-Fi with 2.4GHz/5GHz dual band support: Improved network stability even in Wi-Fi-crowded homes
- Includes two digital Optical inputs for your TV or digital device: The M-CR612 automatically detects the signal input from your TV and outputs elevated sound
- Works with your TV remote: Program the M-CR612 to work with your TV remote and easily adjust volume up, volume down, mute and source selection



because music matters

marantz®

M-CR612

NETWORK CD RECEIVER FEATURING HEOS, FM/AM, *BLUETOOTH*®, AIRPLAY 2 AND VOICE CONTROL COMPATIBILITY



Design and specifications are subject to change by Marantz without notice.

FEATURES	M-CR612
High quality power output	2 x 60W
CD compatibility: CD / CD-R/-RW / WMA / MP3	• / • / • / •
Tuner: AM / FM	• / •
HEOS Multiroom & Streaming	•
Online service (HEOS)	Spotify Connect, Amazon Prime, Deezer Premium+, iHeart Radio, Pandora, SiriusXM, Sound Cloud, Tidal
Streaming Audio from computer	•
AirPlay 2	•
Internet Radio	Tune In
Voice Control - Works with Amazon Alexa	•
Voice Control - Google Assist / Apple Siri	• / •
Voice Control - Microphone Built-in	-
Bluetooth	•
Ethernet / WiFi 2.4 GHz (11 b/g/n) / WiFi 5GHz (11 a/n)	• / • / •
WiFi setup: WPS / WiFi Sharing	• / •
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV / AIFF / DSD	• / • / • / • / •
DSD Audio	2.8 / 5.6 MHz
FLAC / WAV / ALAC	192kHz / 24bit
Gapless Playback - FLAC / WAV / DSD	• / • / •
Remote App: iDevice / Android	• HEOS App
Tone control: Bass / Treble / Balance	• / • / •
Low Noise OLED Display	3 line
Front illumination	Blue, White, Green, Orange
Alarm: Once / Daily / Programmable / Timer	• / • / • / •
IR Learning for TV Remote	•

INPUTS / OUTPUTS	
Analog in / Out	1 / 1
Digital optical In	2
USB input: type A	1 (rear)
Subwoofer PreOut	1
Headphone Out	•
Speaker A / B	•
Speaker binding Post	Screw type

SPECIFICATIONS	
AUDIO SECTION	
Power Output (6 ohm, 1kHz)	60W
Number of channels	2
Bi-Amping / Speaker A+B / Parallel BTL	• / • / •
Frequency Response	10Hz - 40kHz
Signal to noise ratio	90dB
Total Harmonic Distortion	0.1

FM SECTION	
Frequency range FM	87.5 - 108 MHz
Signal to Noise Ratio FM (Mono/Stereo)	70/70dB
Total Harmonic Distortion FM (Mono/Stereo)	0.4/0.4%

GENERAL	
Available color	Black
MENU languages	EN / FR / ES
Remote Control	RC014CR
Power Consumption	55W
Standby Consumption	0.3W
Dimensions: W x H x D (in)	11.02 x 11.93 x 4.37
Weight (lbs)	7.28

UPC		
M-CR612/U1B	Black	699927711658

Sound United LLC
North America Regional Headquarters
1 Viper Way
Vista, CA 92081

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

* All specs can be subject to change.