marantz



SACD 30n

Networked SACD / CD player with HEOS® Built-in

A master-tuned, elegantly designed SACD / CD player with integrated digital sources. Includes Marantz Musical Mastering processing and a very low-noise, crystal-clear pre-amplifier. The SACD 30n supports a wide variety of high-resolution files and streaming services. Pairs with the MODEL 30 integrated amplifier. Your music always sounds better on a Marantz.

- Best Marantz audio quality from any digital source.
- Tuned with passion by the Marantz Sound Master.
- Marantz CD/SACD transport mechanism reduces interference.
- Marantz HDAM circuitry for clean, optimal dynamics.
- DAC Mode, SACD/CD player, streamer and very low-noise pre-amplifier.
- Marantz Musical Mastering for pure analog audio from any digital source.
- Fixed level and independent variable output.
- Multiple inputs and outputs for component flexibility.
- HEOS® Built-in for whole-home integration and streaming options.
- Controllable by the leading voice control services.
- Designed to complement the MODEL 30 integrated amplifier.
- Available in Black and Silver Gold.



The Most Musical Sound

SACD 30n Technical Specifications

Network Engine		HEOS
-	aia filo atroamina	WMA / MP3 / AAC
Computer music file streaming		WMA / MP3 / AAC WAV192/24 / FLAC 192/24 ALAC 192/24 DSD 2.8/5.6
DLNA	Version	(compatibility)
	DMP (Digital Media Player) DMR (Digital Media Renderer)	(compatibility) (compatibility)
Gapless Playb	ack (Music Server, USB A)	yes
Internet Radio (TuneIn)		(FLAC, WAV, ALAC, DSD) ves
AirPlay		yes (2)
Cloud Music S	iervice	Spotify Connect(except CN), Amazon Prime(except CN), Deezer Premium+(EU, NA), iHeart Radio(NA), Napster(EU, NA), Pandora(NA), Sirius/M(NA), Sound Cloud(All), Tidal(EU,NA), Mood Mix(EU, NA), AWA(JP), QQ music(CN)
Wi-Fi	WPS (Wi-Fi Protected Setup) WMM	yes 2.4GHz(11b/g/n), 5GHz(11a/n PBC only yes
	OFF mode	yes
Bluetooth	OFF mode	yes (SBC.AAC) yes
USB		yes
USB-B Input	USB-DAC	1 (PCM:Up to 384kHz/32bit,
000-011/000	Asynchronous mode	T (PCM:0p to 384kHz/32bit, DSD:0p to 11.2MHz) yes
	Isolator	yes (and digital inputs)
USB-A Input	USB Mass Storage Audio Music File	(at Rear) WMA / MP3 / AAC / WAV192/24 / FLAC 192/24 / ALAC 96/24 / DSD 2.8/5.6
	Support format	FAT 16/32, NTFS
Audio		
Audio Circuit		HDAM
D/A Converter		MMM Conversion
Power Transformer		Toroidal
Dither		Not selectable
Noise Shaper		Not selectable
Digital Filter		MMM-Stream (Filter 1, 2)
Jitter Reducer		yes (FLAC, WAV, ALAC, DSD)
Dual Clock (fo	r 44.1/48kHz)	yes
Headphone Amp		HDAM-SA2 Full discrete headphone amp circuit, Gain setting (Low/Mid/ High), Auto detected plug on/off and turn on/off HP AMP
Terminal		
Audio Digital IN COAX IN		1
And Distant	OPTICAL IN	2
Audio Digital (OUT COAX OUT OPTICAL OUT	1 (on/off switchable) 1 (on/off switchable)
Analog Audio		1 L/R independent, gold plated
USB	USB-A IN USB-B IN	high grade brass terminals Rear x 1 Rear x 1
Ethernet	555 5 IN	yes
Wi-Fi antenna		yes yes (removable rod antenna)
Headphone		yes (06.3 x1)
UI		yes (#0.0 x1)
Remote APP		HEOS app
Display		OLED 3-line display
		(Dimmer 4-levels)
Language		(EU9:EN/DE/FR/IT/NL/ES/SE/ PL/RU, JP:JP/EN, NA:EN/FR/ES, CN:CN/EN)





Design and specifications are subject to change by Marantz without notice.

www.marantz.com

