MODEL # VA26 Video Amplifier & Video Switcher



	Pacific Accessory Corporation
Wire Color	Function
Red:	connect to switched +12 volt source (Accessory)
Black:	connect to chassis ground
Orange:	connect to positive trigger device (positive trigger)
Gray:	connect to negative trigger device (negative trigger)
Notes:	Video amplifier can drive up to 6 monitors.
	🛡 Use either orange (+) or gray (-) triggger NOT BOTH !!!
	• If using the VA26 primarly as a video amplifier with only
	one video input, then the orange/gray wires are not needed and
	Video 1 becomes the primary input.
	video i becomes the primary inpath
	Video 1-Input
Vido	
vide	
Gray-Negativ	/e Trigger • • • • • • • • • • • • • • • • • • •
Orange-Positiv	/e Trigger • • • • • • • • • • • • • • • • • • •
	Red-Acc. +12V
	Black-Ground
	Pacific Accessory Corporation
	Video 1-Output
	Video 2-Output
	Video 3-Output
	Video 4-Output
	Video 5-Output
	Video 6-Output
	Decific Accessory Composition to the upport @co2per.com
	Pacific Accessory Corporation-techsupport@go2pac.com 1502 S. Santa Fe Street Santa Ana, CA 92705
	Voice 714-835-3022 FAX 714-835-3233