

## SONANCE

## **Volume Controls**

- 12-step, high-quality autoformer design combines premium performance with great reliability.
- Available in rotary or slider formats.
- Allows volume control for individual pairs of speakers connected to a common amplifier.
- Decoraâ, ¢ style can be ganged together with other low voltage devices.



## VC60S

Power Handling 60W RMS max input/channel

Total Attenuation -42 dB

Attenuation Steps Top 6 steps are -3dB per step; lowest four steps are -6dB

per step; last step is OFF position.

Speaker Impedance 8 ohms

Frequency Response 20Hz - 20kHz ±1dB

Connections Quick-disconnect screw terminal, 20-14 AWG wire

capacity.

Design Decora Style Slider

Dimensions (WxHxD) 15/8" x 4" x 3" (41mm x 102mm x 76mm)

Shipping Weight 2 lbs. (0.9kg)