

**WBM6T** 6.5", white housing, 70V/25V

**WBM6TA** 6.5", white housing, Built-in 10W amplifier

### Features

- Speaker is completely enclosed in a sturdy metal enclosure
- Design greatly reduces chance of damage to or tampering with speaker
- WBM6TA is ideal for surveillance audio applications



| Speaker Specifications     | WBM6T  | WBM6TA                        |
|----------------------------|--|-------------------------------|
| RMS Output Power           | 20W  |                               |
| Max Output Power           | 40W  |                               |
| Power                      | 70V/25V Transformer  | 12VDC (not included-use PSW5) |
| Transformer Settings       | 6W, 3W, 1.5W   | N/A                           |
| Sensitivity (1W/1M)        | 87dB   |                               |
| Maximum SPL (Pmax/1M)      | 103dB  |                               |
| Impedance                  | 8 Ohms   |                               |
| Magnet Material and Weight | Ferrite, 10 oz   |                               |
| Frequency Response Range   | 110Hz - 20kHz  |                               |
| Dispersion                 | 180°   |                               |
| Driver                     | 6.5" polypropylene cone, rubber edge woofer, .5 PEI dome tweeter |                               |
| Amplifier                  | N/A  | 10W                           |
| Input                      | N/A  | 3.5mm                         |

### Operating Specifications

|                         |                                |       |
|-------------------------|--------------------------------|-------|
| Dimensions              | 7.7" (L) x 7.7" (W) x 3.2" (H) |       |
| Speaker Weight          | 6 lbs                          | 7 lbs |
| Speaker Body Material   | Metal                          |       |
| Speaker Grille Material | Metal                          |       |

**NDAA**  
COMPLIANT

\*Products are in compliance with NDAA Section 889 Part B Guidelines

### Optional Accessories



**PSW5**  
12VDC  
Power Supply