





# 2-Port DVI USB KVM Switch Kit with Audio TK-204UK (v2.1R)

The 2-Port DVI USB KVM Switch Kit with Audio manages two computers with one set of console controls. Control two computers with DVI and USB ports at the touch of a button with one set of microphone / speakers, USB keyboard, USB mouse, and DVI monitor.

Simply plug everything in to start sharing your HD DVI monitor with two Mac or Windows computers. No need for additional cabling, all required cables are included. Network printers, storage drives, flash drives and more by connecting to the two bonus USB ports on the front of the switch. Listen to music on one computer while working on the other. Switch between computer by pressing the convenient switch button or by programming shortcut Hotkey commands.

#### PRODUCT OVERVIEW

- · Manage two PCs or Macs with one set of console controls
- · Share an HD DVI monitor with two computers
- · Two bonus USB ports to network printers, storage devices, and more
- · Listen to music on one computer while working on the other
- · All required cables are included

#### **FEATURES**

- 2 x USB keyboard and mouse ports
- 2 x bonus USB 2.0 ports
- · 2-way audio support for uninterrupted multimedia experience across multi-platforms
- · Independent simultaneous switching of both PC and audio channels
- · Advanced keyboard and mouse support
- · Multi-platform support for Windows, Mac, and Linux
- · Hot-plug PCs without powering down the KVM switch (Window OS)
- Digital video resolution up to 1920 x 1200 and analog video resolution up to 2048 x 1536
- · Integrated High-Bandwidth Digital Content Protection (HDCP) and Transition Minimized Differential Signaling (TDMS)
- · No CD installation required—simply plug and go
- · 2-year limited warranty

## 2-Port DVI USB KVM Switch Kit with Audio





### **SPECIFICATIONS**

HARDWARE		
Connections	• 2 computers	
Standard	DVI-I and DVI-D Compliant     USB 2.0 compliant	
PC Port Connector	<ul> <li>2 x USB type B</li> <li>2 x DVI-I (integrated speaker / microphone support)</li> </ul>	
Console Port Connector	<ul> <li>2 x USB type A (keyboard and mouse)</li> <li>2 x USB type A (USB 2.0 devices)</li> <li>1x DVI-I single link</li> <li>1 x 3.5 mm speaker jack</li> <li>1 x 3.5 mm microphone jack</li> </ul>	
Cable	<ul> <li>2 x detachable DVI / speaker and microphone combo cable</li> <li>2 x USB type A to type B cable</li> </ul>	
PC Selection	Push button, keyboard Hotkey commands (Windows only)	
LED	Green: Computer 1     Blue: Computer 2	
VGA Resolution	1920 x 1200 (digital)     2048 x 1536 (analog)	
Power	<ul> <li>Input: 100~240 VAC, 50~60Hz</li> <li>Output: 5V DC, 2A external power adapter</li> </ul>	
Dimensions	• 165 × 75 × 33 mm (6.5 x 3.0 x 1.3 in.)	
Weight	• 160 g (5.6 oz)	
Temperature	<ul> <li>Operating: 0°C ~ 40°C (32° ~104°F)</li> <li>Storage: -20°C ~ 60°C (-4° ~ 140°F)</li> </ul>	
Humidity	Max 90% (Non-condensing)	
Certifications	• CE, FCC	

## 2-Port DVI USB KVM Switch Kit with Audio

TK-204UK (v2.1R)



#### **NETWORKING SOLUTIONS**



#### PACKAGE CONTENTS

TK-204UK
Quick Installation Guide
2 x DVI / Audio combo KVM cable (1.2 m / 4 ft.)
2 x USB type A to type B cable (1.2 m / 4 ft.)
Power Adapter (5V DC, 2A)

#### RELATED PRODUCTS

TK-214i	2-Port DVI USB KVM Switch Kit with Audio
TK-217i	2-Port USB KVM Switch
TK-209K	2-Port USB KVM Switch Kit w/ Audio

#### **CONTACT INFORMATION**

#### TRENDIET

20675 Manhattan Place, Torrance, CA 90501 USA

Tel: 1-310-961-5500 Fax: 1-310-961-5511 Web: www.trendnet.com Email: sales@trendnet.com 1-888-326-6061



